

## General Description

The LTA082H is a cost-effective industry-standard operational amplifier of low power, 40 V wide supply voltage, low noise, rail-to-rail output operational amplifiers capable of operating on supplies ranging from +4.5 V ( $\pm 2.25$  V) to +40 V ( $\pm 20$  V). The LTA082H offers outstanding dc precision and ac performance, including low offset ( $\pm 1$  mV typically), low offset drift ( $\pm 2$   $\mu$ V/ $^{\circ}$ C typically), 5.25 MHz bandwidth, and 21 nV/ $\sqrt{\text{Hz}}$  input voltage noise density at 10 kHz. Unique features make the LTA082H high-performance operational amplifiers for high-voltage industrial applications.

The robust design of the LTA082H provides ease-of-use to the circuit designer: integrated RF/EMI rejection filter and high electro-static discharge (ESD) protection. The LTA082H are optimized for operation at voltages from +4.5 V ( $\pm 2.25$  V) to +40 V ( $\pm 20$  V) over the extended temperature range of 40  $^{\circ}$ C to +125  $^{\circ}$ C.


## Features and Benefits

- Wide Supply:  $\pm 2.25$  V to  $\pm 20$  V, 4.5 V to 40 V
- Low Offset Voltage:  $\pm 1$  mV typically
- Low Offset Voltage Drift:  $\pm 2$   $\mu$ V/ $^{\circ}$ C
- High Common-Mode Rejection: 105 dB
- Gain Bandwidth: 5.25 MHz
- Slew Rate: 9 V/ $\mu$ s
- Low Noise: 21 nV/ $\sqrt{\text{Hz}}$  at 10 kHz
- Low Bias Current:  $\pm 5$  nA over the extended temperature range
- Rail-to-Rail Output

## Applications

- Tracking Amplifier in Power Modules
- Merchant Power Supplies
- High-Side and Low-Side Current Sensing
- Battery-Powered Instruments
- Programmable Logic Controllers
- Solar energy: string and central inverter
- Motor drives: AC and servo drive control and power stage modules
- Single phase online UPS
- Three phase UPS
- Pro audio mixers

## Pin Configuration (Top View)



## Pin Description

Symbol	Description
-IN	Inverting input of the amplifier. The voltage range is from $V_{S-}$ to $V_{S+} - 1.5$ V.
+IN	Non-inverting input of the amplifier. This pin has the same voltage range as -IN.
+ $V_S$	Positive power supply. The voltage is from 4.5 V to 40 V. Split supplies are possible as long as the voltage between $V_{S+}$ and $V_{S-}$ is from 4.5 V to 40V.
- $V_S$	Negative power supply. It is normally tied to ground. It can also be tied to a voltage other than ground as long as the voltage between $V_{S+}$ and $V_{S-}$ is from 4.5 V to 40 V.
OUT	Amplifier output.
NC	No connection

## Ordering Information <sup>(1)</sup>

Type Number	Package Name	Package Quantity	Eco Class <sup>(2)</sup>	Marking Code <sup>(3)</sup>
LTA082HXS8/R8	SOIC-8L	Tape and Reel, 4 000	Green (RoHS & no Sb/Br)	HV082

- (1) Please contact to your Linearin representative for the latest availability information and product content details.
- (2) Eco Class - The planned eco-friendly classification: Pb-Free (RoHS) or Green (RoHS & Halogen Free).
- (3) There may be multiple device markings, a varied marking character of "x", or additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.

## Limiting Value - In accordance with the Absolute Maximum Rating System (IEC 60134).

Parameter	Absolute Maximum Rating
Supply Voltage, $V_{S+}$ to $V_{S-}$	60 V
Signal Input Terminals: Voltage, Current	$-V_S - 0.3$ V to $+V_S + 0.3$ V, $\pm 10$ mA
Output Short-Circuit	Continuous
Storage Temperature Range, $T_{stg}$	$-65$ to $+150$ °C
Junction Temperature, $T_J$	150 °C
Lead Temperature Range (Soldering 10 sec)	260 °C

## ESD Rating

Parameter	Item	Value	Unit
Electrostatic Discharge Voltage	Human body model (HBM), per MIL-STD-883J / Method 3015.9 <sup>(1)</sup>	2 000	V
	Charged device model (CDM), per ESDA/JEDEC JS-002-2014 <sup>(2)</sup>	1 000	

- (1) JEDEC document JEP155 states that 500-V HBM allows safe manufacturing with a standard ESD control process. Manufacturing with less than 500-V HBM is possible if necessary precautions are taken.
- (2) JEDEC document JEP157 states that 250-V CDM allows safe manufacturing with a standard ESD control process. Manufacturing with less than 250-V CDM is possible if necessary precautions are taken.

## Electrical Characteristics

$V_S = 4.5 \text{ V to } 40 \text{ V}$ ,  $T_A = +25 \text{ }^\circ\text{C}$ ,  $V_{CM} = V_{OUT} = V_S/2$ , and  $R_L = 10 \text{ k}\Omega$  connected to  $V_S/2$ , unless otherwise noted. Boldface limits apply over the specified temperature range,  $T_A = -40 \text{ }^\circ\text{C to } +125 \text{ }^\circ\text{C}$ .

Parameter	Symbol	Conditions	Min.	Typ.	Max.	Unit
<i>OFFSET VOLTAGE</i>						
Input offset voltage	$V_{OS}$			$\pm 1$	$\pm 4$	mV
Offset voltage drift	$V_{OS \text{ TC}}$	$T_A = -40 \text{ to } +125 \text{ }^\circ\text{C}$		$\pm 2$		$\mu\text{V}/^\circ\text{C}$
Power supply rejection ratio	PSRR	$V_S = 4.5 \text{ to } 40 \text{ V}$ , $V_{CM} = 0.1 \text{ V}$		5		$\mu\text{V}/\text{V}$
		$T_A = -40 \text{ to } +125 \text{ }^\circ\text{C}$		10		
<i>INPUT BIAS CURRENT</i>						
Input bias current	$I_B$			100		pA
		$T_A = -40 \text{ to } +85 \text{ }^\circ\text{C}$		950		
		$T_A = -40 \text{ to } +125 \text{ }^\circ\text{C}$		5		
Input offset current	$I_{OS}$			5		nA
<i>NOISE</i>						
Input voltage noise	$V_n$	$f = 0.1 \text{ to } 10 \text{ Hz}$		9		$\mu\text{V}_{\text{P-P}}$
Input voltage noise density	$e_n$	$f = 1 \text{ kHz}$		37		$\text{nV}/\sqrt{\text{Hz}}$
		$f = 10 \text{ kHz}$		21		
Input current noise density	$I_n$	$f = 1 \text{ kHz}$		80		$\text{fA}/\sqrt{\text{Hz}}$
<i>INPUT VOLTAGE</i>						
Common-mode voltage range	$V_{CM}$		$-V_S$		$+V_S - 1.5$	V
Common-mode rejection ratio	CMRR	$V_S = 40 \text{ V}$ , $V_{CM} = 0 \text{ to } 38 \text{ V}$		105		dB
		$V_{CM} = 0.1 \text{ to } 38 \text{ V}$ , $T_A = -40 \text{ to } +125 \text{ }^\circ\text{C}$		95		
<i>INPUT IMPEDANCE</i>						
Input capacitance	$C_{IN}$	Differential		2.0		pF
		Common mode		3.5		
<i>OPEN-LOOP GAIN</i>						
Open-loop voltage gain	$A_{VOL}$	$V_S = 40 \text{ V}$ , $V_O = 0.1 \text{ to } 39.9 \text{ V}$		126		dB
		$T_A = -40 \text{ to } +125 \text{ }^\circ\text{C}$		118		
		$V_S = 5 \text{ V}$ , $V_O = 0.1 \text{ to } 4.9 \text{ V}$		116		
		$T_A = -40 \text{ to } +125 \text{ }^\circ\text{C}$		108		
<i>FREQUENCY RESPONSE</i>						
Gain bandwidth product	GBW			5.25		MHz
Slew rate	SR	$V_S = 40 \text{ V}$ , $G = +1$ , $10 \text{ V step}$		9		$\text{V}/\mu\text{s}$
Total harmonic distortion + noise	THD+N	$G = +1$ , $f = 1 \text{ kHz}$ , $V_O = 3 \text{ V}_{\text{RMS}}$		0.0002		%
Settling time	$t_S$	To 0.1%, $V_S = 40 \text{ V}$ , $G = +1$ , $5 \text{ V step}$		1.6		$\mu\text{s}$
		To 0.01%, $V_S = 40 \text{ V}$ , $G = +1$ , $5 \text{ V step}$		3.5		
Overload recovery time	$t_{OR}$	$V_{IN} \times \text{Gain} > V_S$		0.6		$\mu\text{s}$

## Electrical Characteristics (continued)

$V_S = 4.5 \text{ V to } 40 \text{ V}$ ,  $T_A = +25 \text{ }^\circ\text{C}$ ,  $V_{CM} = V_{OUT} = V_S/2$ , and  $R_L = 10 \text{ k}\Omega$  connected to  $V_S/2$ , unless otherwise noted. Boldface limits apply over the specified temperature range,  $T_A = -40 \text{ }^\circ\text{C to } +125 \text{ }^\circ\text{C}$ .

Parameter	Symbol	Conditions	Min.	Typ.	Max.	Unit
<i>OUTPUT</i>						
High output voltage swing	$V_{OH}$	$V_S = \pm 20 \text{ V}$ , $R_L = 10 \text{ k}\Omega$		$+V_S - 95$		mV
		$V_S = \pm 20 \text{ V}$ , $R_L = 2 \text{ k}\Omega$		$+V_S - 255$		
Low output voltage swing	$V_{OL}$	$V_S = \pm 20 \text{ V}$ , $R_L = 10 \text{ k}\Omega$		$-V_S + 60$		mV
		$V_S = \pm 20 \text{ V}$ , $R_L = 2 \text{ k}\Omega$		$-V_S + 240$		
Short-circuit current	$I_{SC}$			$\pm 45$		mA
<i>POWER SUPPLY</i>						
Operating supply voltage	$V_S$	$T_A = -40 \text{ to } +125 \text{ }^\circ\text{C}$	4.5		40	V
Quiescent current (per amplifier)	$I_Q$	$V_S = 5 \text{ V}$		2.05		mA
		$V_S = 40 \text{ V}$		2.75		
<i>THERMAL CHARACTERISTICS</i>						
Operating temperature range	$T_A$		-40		+125	$^\circ\text{C}$
Package Thermal Resistance	$\theta_{JA}$	SOIC-8L		125		$^\circ\text{C/W}$